

Designo™ Room Automation

DXR2 room automation stations, BACnet/IP and BACnet/SC, 24 V

DXR2.E12P



- Compact, programmable room automation stations for HVAC, lighting, and shading.
- BACnet IP Ethernet Communication (BTL certified).
- BACnet Secure Connect communication
- 2 port Ethernet switch.
- KNX PL-Link bus to connect sensors, actuators, and operator units (including bus power).
- USB interface.
- Operating voltage AC 24V.
- Internal 0...500 Pa (0...2 in WC) differential pressure sensor
- Mounted on standard DIN rails or on the wall.
- Plug-in terminal blocks.

Features

- Total Room Automation applications combining multiple disciplines (HVAC, lighting, blinds/shading) into one comprehensive solution.
- BTL Listed as a BACnet Advanced Application Controller (B-AAC) device.
- Fully programmable using block programming.
- Proven, pre-loaded applications.
- Operational modes (Comfort, Standby, Economy, Protection, and so on).

Preconfigured applications

Variable Air Volume (VAV) or Constant Volume (CV)

- VAV Cooling Only
- VAV with staged Electric Heat
- VAV with Hot Water
- VAV with Hot Water and Supply Temp Control

Dual Duct Variable Air Volume (VAV)

- VAV Dual duct – Cold duct and Hot duct with configurable ventilation delivery with hot water or electric heating coils and radiator
- VAV Dual duct – Cold duct and dedicated ventilation duct with DCV with hot water or electric heating coils and radiator

VAV with Fan Powered Boxes (FPB)

- VAV Series FPB with staged Electric Heat
- VAV Series FPB with Hot Water
- VAV Series FPB with Hot Water and Supply Temp Control
- VAV Parallel FPB with staged Electric Heat
- VAV Parallel FPB and Hot Water
- VAV Parallel FPB with Hot Water and Supply Temp Control

Chilled Beam

- Chilled Beam Passive Heating and Cooling with Hot Water Radiator
- Chilled Beam Active Heating and Cooling VAV with Hot Water Radiator
- Chilled Beam Active Heating and Cooling VAV with Electric 1-Stage Radiator

Additional Applications

- Electrical terminal heating coils, PWM, 1...3 stages or analog
- Series or Parallel fans, 1...3 stages or analog
- Chill water coils and heating/cooling coils (2-pipe or 4-pipe)
- Supply/Extract (Exhaust) airflow tracking and control
- Radiant ceiling including Chilled beams, cooling, heating and heating/cooling (2-pipe or 4-pipe) control
- Radiator/Baseboard: hot water, steam or electric
- Lighting – up to four separated or overlapping zones
 - Manual switching and dimming
 - Occupancy control and Vacancy control
 - Automatic Daylight Harvesting - step or constant level control
 - Stairwell lighting
 - Scene control
- Blinds – one or two separate zones

- Manual control: Up, Down, Predefined positions
- Occupancy control and Vacancy control
- Glare Protection
- Energy efficiency functions including solar radiation optimization
- Slat angle
- Scene control

Pre-loaded Application Options

- Separate maximum and minimum flow setpoints for both heating and cooling control.
- Separate minimum ventilation flow setpoints for each occupancy mode.
- CO2 sensor and Demand control ventilation with maximum ventilation flow setpoint.
- Flexible occupancy modes: Comfort, Pre-Comfort, Economy and Protection.
- Supply (discharge) air temperature control for modulating heating or cooling coils.
- Configurable occupancy sensor control.
- Relative humidity sensor and room dew point calculation.
- Greenleaf energy efficiency determination and display.
- Configurable plant operating modes (heating, cooling, warm up, cool down, flush/purge, and so on).

Functions

The selected application and its parameters as well as input and output configuration determine the room automation station's functionality.

A detailed description of functionality is available in the ABT (Automation Building Tool) online help.

Communication

- 2-Port Ethernet switch for cost-effective cabling via line topology.
- USB connection for service and commissioning, firmware download, and LAN access.
- The following functions are available with the KNX PL-Link bus:
 - Communication with room operator units, switches, sensors, actuators, and luminaires.
 - Plug-and-play connection of Siemens field devices with KNX PL-Link.
 - Integration of common devices using KNX S-Mode (ETS engineering required).

LED indication

LED	Color	Activity	Function
RUN	Green	Steady ON	Device is ready for operation
		Steady OFF	Device is not powered
		Regular flashing	Start-up or the program is stopped
	Red	Steady OFF	OK
		Steady ON	Program error Communications error (KNX PL-Link) Hardware fault
		Rapid flashing	Wrong or corrupt software No application loaded
		Blinking per wink command	Physical device identification

LED	Color	Activity	Function
SVC (Service button)	--	Short press	Physical identification on the network
	--	Factory reset	1. Power off the device. 2. Power on the device. 3. Wait until the RUN LED lights up and turns off again, then press the Service button. 4. Keep the Service button pressed until the RUN LED lights up, then release the button. The device restarts. 5. Wait until the device has fully started – unconfigured (green RUN LED on, flashes red)

Type summary

Product Number	SSN	Description	Inputs	Outputs
DXR2.E12P-102B (Version with 30 data points)	S55376-C126	DXR2.E12P Room Automation Station	1 DI, 2 UI, 1 ΔP sensor	6 DO Triacs, 2 AO 0 to 10V
DXR2.E12P-102K (Version with 30 data points)	S55376-C156	Smoke Control DXR2.E12P Room Automation Station	1 DI, 2 UI, 1 ΔP sensor	6 DO Triacs, 2 AO 0 to 10V
DXR2.E12PX-102B (Version with 60 data points*)	S55374-C252	DXR2.E12PX Room Automation Station	1 DI, 2 UI, ΔP sensor	6 DO Triacs, 2 AO 0 to 10V
DXR2.E12PX-102K (Version with 60 data points*)	S55376-C157	Smoke Control DXR2.E12PX Room Automation Station	1 DI, 2 UI, ΔP sensor	6 DO Triacs, 2 AO 0 to 10V

* 60 data point DXRs are typically used for Designo Total Room Automation projects.

Accessories

Product Number	Designation
985-124	499 ohm Resistor Kit

Product Documentation

Topic	Title	Document ID
Installation and mounting	DXR Installation Instructions	A6V10550039
Global datasheet*	DXR2 24V IP DXR2 24V MS/TP	N9205 N9207

Topic	Title	Document ID
Setup and commissioning	DXR VAV Start-up Procedures DXR FPB Start-up Procedures DXR FCU Start-up Procedures Balancing Procedures	A6V10665935 A6V10665938 A6V10665941 A6V10665943
Room Unit Datasheet	Wall mounted	A6V10394781
BTL listing	DXR PIC Statement	A6V10665948

* Please see the Global datasheets for additional information not found in this submittal sheet.

Technical data

Housing

Color	RAL 7035 (light-gray)
Dimensions	180 mm (7.09 in) x 104.5 mm (4.11 in) x 59.5 mm (2.34 in)
Weight Packaging	ca. 340 g (11.99 oz) ca. 40 g (1.41 oz)

Function data

Communication

A/D Resolution (analog in)	14 Bits
D/A Resolution (analog out)	12 Bits

Power data

Power supply

Operating voltage	AC 24V -15%/+20%
Frequency	50/60 Hz
Internal fuse	4 A irreversible
Transformer with secondary current limitation of max. 10 A or external secondary current fuse Non-renewable fuse Circuit breakers	Max. 10 A, slow Max. 13 A, characteristic B, C, D as per EN 60898

Apparent power (VA) for transformer design						
Base Model	Base load	Max. load Triac output AC 24V~ 0.25 A each	Max. load all Aux. outputs AC 24V~	Max. load KNX PL-Link (at 50 mA)	Max. load DC 24V+ (2.4 W) ¹	Max. Allowed Power consumption including connected field devices
DXR2.E12P	8	6 x 6 = 36	12	4	-	60



NOTE:

To calculate the total VA, add the Base Load + the number of Triacs + field supplies+ KNX PL-Link devices.

This cannot exceed the maximum power consumption. See the *Wiring Guidelines* for more information.

Inputs

Analog Inputs		
Resistance sensor	Temperature measurement	Voltage measurement
AI 1000 Ω	AI PT1K 375 (NA)*)	AI 0 to 10V
AI 2500 Ω	AI PT1K 385 (EU)*)	AI 0 to 10V (0 to 100%)
AI 10 KΩ	AI (LG-)Ni1000*)	
AI 100 KΩ	AI Ni1000 DIN*)	
	AI T1 (PTC)*)	
	AI NTC10K (Type II)**)	
	AI NTC100K**)	

* A fixed value of 1 Ω is calibrated to correct line resistance.

** Configurable default.

Digital Inputs	
Contact voltage	Universal input: 18V Digital input: 21V
Contact current	Universal input: 1.2 mA; 7.4 mA initial current Digital input: 1.6 mA; 9.4 mA initial current
Contact resistance for closed contacts	Max. 100 Ω
Contact resistance for open contacts	Min. 50 kΩ

Differential pressure sensor (inputs P1+, P1-)	
Connections (nipple diameter)	Dia. 5.2 mm (0.20 in)
Measuring range	0 to 500 Pa (0 - 2.01 in WC)
Overload range	0 to 100 kPa (0 - 402 in WC)
Measuring range accuracy	4.5%
Zero point accuracy	0.2 Pa
Resolution	12 bit

Outputs

Analog Outputs	
0 to 10V	Max. 1 mA

Digital Outputs	
Type (Switching outputs triacs)	High side The Triac closes the contact to AC 24V
Switching voltage	AC 24V
Permissible load	250 mA/6 VA per output (cos phi 0.35) (500 mA/12 VA per output with PWM*)
Protection	Short-circuit proof

Connections

Interfaces	
Ethernet	Plugs: 2 x RJ45, screened Interface type: 10Base-T/100BASE-TX, IEEE 802.3 compliant Bitrates: 10/100 Mbps, autosensing Protocol: BACnet over UDP/IP
USB (2.0)	Plug: Type B Data rate: 12 Mbps
KNX	Type: KNX TP1 PL-Link, galvanic isolation Baud rate: 9.6 Kbps Bus power: 50 mA Short-circuit proof Protection against faulty wiring at max. AC 24V

Wiring connections	
Pluggable screw terminals	Copper wire or copper strands with ferrules 1 x 0.6 mm dia. to 2.5 mm ² (22 to 14 AWG) or 2 x 0.5 mm dia. to 1 mm ² (24 to 18 AWG) Copper strands without ferrules 1 x 0.6 mm dia. to 2.5 mm ² (22 to 14 AWG) or 2 x 0.5 mm dia. to 1.5 mm ² (24 to 16 AWG)
Slotted screws	Small 1/8" blade, tightening torque 0.6 Nm (0.44 lb-ft)
Wiring lengths for signals	KNX PL-Link 80 m (260 ft) with internal bus power or 300 m (990 ft) with external power supply Ethernet 100 m (330 ft) Signal lines 80 m (260 ft) For inputs AI 100 KΩ, AI NTC10K, AI NTC100K: 30 m (100 ft) or 80 m (260 ft), if shielded.

KNX/PL-Link Network and Power Wiring.*	
Cable configuration	1 or 2 twisted pair - Pair 1 red/black - Pair 2 yellow/white
Gauge	20 AWG (solid copper)
Twists per foot	4 Minimum
Capacitance	30 pF/foot or less
Shields	100% foil with drain wire
UL type	300Vrms, CMP (75 °C or higher)
CSA type	300Vrms, FT6 (75 °C or higher)

* Alternative 18 AWG STP CMP (Belden 6320FE 8771000)

Conformity

 CAUTION	
	National safety regulations Failure to comply with national safety regulations may result in personal injury and property damage. Observe national provisions and comply with the appropriate safety regulations.

Ambient Conditions and Protection classification	
Climatic ambient conditions • Transport and storage • Operation	• Temperature -25 to 70°C (-13 to 158°F) Air humidity 5 to 95% rh. • Temperature -5 to 45°C (23 to 113°F)/ -5 to 50°C (23 to 122°F) Air humidity 5 to 95% rh.

Standards, Directives and Approvals	
UL Listing	UL 916 PAZX - Conforms to UL916 9th and 10th Edition. UL 864 UUKL Smoke Control Equipment - Conforms to UL864 9th and 10th Edition. (Smoke Control 'K' variant only)
Suitable for plenum area installation	UL1995
Federal Communications Commission	FCC CFR 47 Part 15 Class B
CSA Compliance and cUL certification	C22.2 No. 205
Environmental compatibility - RoHS Compliant	The product environmental declaration contains data on environmentally compatible product design and assessments (composition, packaging, environmental benefit, and disposal).
BACnet BTL Listing	BTL-AAC
CEC Title 24 Supported	—
ASHRAE Guideline 36 Supported	—
ASHRAE 90.1 Supported	—
Quality	ISO 9001 (Quality)

Issued by
Siemens Industry, Inc.
Smart Infrastructure
1000 Deerfield Pkwy
Buffalo Grove IL 60089
+1 847-215-1000

© Siemens 2021
Technical specifications and availability subject to change without notice.